

## Sprinter Van 3 Camera Kit - Manual

### Included in kit :

- Glass Mount 3 Input Rearview mirror with Glass Mount Adapter
- Brake light Replacement Camera
- (2) Side View Cameras
- 32ft Cable (10) 4-Pin Extension Cable
- (2) Time Delay Relay with Socket (Set to 5 seconds)
- 6 Ft RCA Cable

### Wiring diagram for relays and Side View Camera:

Connect the black wire of the Side View Camera to ground and the red wire to the green (87) wire of the relay.

Connect white (86) to the corresponding turn signal wire  
**(Left Side View Camera to positive left turn signal wire of vehicle and right Side View Camera to positive right turn signal wire of vehicle)**

Connect red (85) to ground

Connect 30 to +12v.

